

## Power Conditioner 12 VDC- 12 VDC DC-DC Power Supply **KT-DC12 & PS-DC12** by Dotworkz, Inc.

## 50 Watt Output 12 VDC DC-DC **Power Conditioner with Half Brick Module**

## Half Brick Pin-Out

Input Range: 9 – 18 VDC No Load Input Current: 50 ma

Full Load Input Current: 4.95 Amps @ 12 VDC


Rated Output: 50 Watts @ 12 VDC Max. Output Current: 4.16 Amps

Efficiency: 84%

Dimensions: 3.1" x 2.5" x 0.5" (L x W x H)


PCB Mounting: 2.8"l x 2.2"w O.C., Hole dia. 0.170"


Weight: 0.24 lbs.




Used for applications to provide level 12 VDC voltage where supply voltage fluctuates. Ideal for:

- \* Mobile NVR Applications such as Xero NVR
- \* Wireless Radios to provide regulation
- \* UPS or Battery Power applications to provide 12 VDC regulation
- \* Regulating "Dirty" Power Sources
- \* KT-DC12 includes Internal Mounting Bracket & Hardware for D-Series Housing







PIN CONNECTION	
Pin	Function
1	+V Input
2	ON/OFF
3	CASE
4	-V Input
5	-V Output
6	-Sense
7	Trim
8	+Sense
9	+Vout

## NOTE:

- Measured From High Line to Low Line.
  Measured From Full Load to Zero Load.
  Logic Compatibility .... Open Collector ref, to -Input.

Module ON . Module OFF ....Open Circuit <0.8Vdc

4. Suffix "N" to the Model Number with Negative Logic Remote ON/OFF